



Standard five station charger models -

- 223-113A Five station charger for Sidekick EX / TX / MTX series pumps, Universal EX / TX / MTX / MA / AZ / MAZ series pumps and AirChek 52 pump
- 223-115A Five station charger for Universal XR series pumps
- 223-119A Five station charger for AirChek 3000 pump

Please read these instructions before using the charger!

Specifications

Model	Input	Output x5	Battery Pack Specification
223-113A	100-240V ~ 50/60Hz	180mA =	NiCd/NiMH 4cell 4.8V 2.0Ah
223-115A	100-240V ~ 50/60Hz	180mA =	NiCd/NiMH 5cell 6.0V 2.0Ah
223-119A	100-240V ~ 50/60Hz	180mA =	NiMH 4cell 4.8V 2.0Ah

Introduction

The SKC Ltd five station chargers provide five charging outputs with a fixed 16 hour constant current charge for SKC NiCd and NiMH battery packs. At the end of the 16 hour charge, the chargers automatically switch each of the five outputs individually to a trickle charging rate to prevent overcharging.

The chargers are supplied with four inter-changeable electrical supply input plugs suitable for use in the United Kingdom, Europe, USA / Canada and Australia / New Zealand.

Warnings

These chargers are designed for use specifically with the stated SKC pump models and are not intended for use with any other SKC or non-SKC products. Use of the charger with unintended products may cause damage to the product and / or the charger.

These chargers must not be used to charge non-rechargeable batteries.

These chargers are for indoor use only, with enclosure rating of IP40, and must therefore be protected against exposure to moisture.

Operating temperature range - 0°C to +40°C, 95% RH non-condensing.

Use of a non-SKC charger to charge SKC pump battery packs may cause damage to the battery pack and / or pump and will void the battery pack and / or pump warranty, also the intrinsic safety rating of the pump may be invalidated.

Charger Operation

1. Select the correct electrical supply input plug for your region and fit it to the charger power supply unit.

2. Plug the charger power supply unit into an electrical supply socket and switch on the electrical supply. The 'power' LED indicator will illuminate red.
3. Plug a charger output connector into the charging socket on a battery pack. The charger output LED indicator will illuminate yellow continuously to indicate that the charger is charging at full rate. Any combination of the five charger outputs may be used simultaneously and battery packs can be connected at any time, as each charger output is individually controlled.
4. After the fixed 16 hour charging period the charger will automatically switch the output to a trickle charging rate, and the output LED indicator will flash on and off to indicate this.
5. It is recommended to disconnect the charger from the battery pack after a period of 24hours to maintain optimum battery life and performance.
6. It is recommended to disconnect the charger from the electrical supply when not in use to save the energy the charger consumes when on standby.

The Waste Electrical and Electronic Equipment

This product is marked with the crossed out wheellie bin symbol, which identifies that it falls within the scope of the EU Directive 2002/96/EC and the 2013 UK Regulations on waste electrical and electronic equipment (WEEE). At the end of it's useful life, this product must be disposed of in an environmentally sound way as detailed in the Directive / Regulations. Please contact your local distributor or SKC Ltd for further details on how to comply with the requirements of the WEEE Directive. SKC Ltd's producer registration number is WEE/KH0054TQ.

Battery Disposal

SKC battery packs fall within the scope of the EU Directive 2006/66/EC and the 2009 UK Regulations on batteries and accumulators and waste batteries and accumulators and equivalent legislation in other regions. Batteries must be collected and treated separately from other waste, and those containing mercury, cadmium and lead are subject to special treatment.

Please contact your local distributor or SKC Ltd for further details on how to comply with the requirements of the Batteries Directive / Regulations. SKC Ltd's batteries producer registration number is BPRN00454.

SKC Limited, 11 Sunrise Park, Higher Shaftesbury Road, Blandford Forum, Dorset, DT11 8ST, **United Kingdom**

Phone: +44 (0) 1258 480188 Email: info@skcltd.com Web: www.skcltd.com



Air Sampling Solutions & Expertise